

**\*\*\*READ & SAVE THESE INSTRUCTIONS \*\*\***  
**ACCESS LIGHTING**  
**MODEL 62089**  
**INSTALLATION & OPERATION INSTRUCTIONS**

(1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE SCREW DRIVER
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE

**Attention:**

*Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.*

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

**NOTE:**

*The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.*

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ Universal Crossbar
- ❖ Mounting Hardware
- ❖ Fixture
- ❖ 1 x 1W White LED pre-installed in the fixture

(4) PREPARE THE FIXTURE

*Refer to attached illustration of fixture parts and assembly.*

**This Fixture can be Hard-Wired to an electrical box, or used as a plug-in.**

**Hardwiring the fixture**

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Remove the cord and plug from the fixture by removing the wire nuts connecting the cord and plug to the fixture wires.
3. Secure the **Mounting Bracket (A)** to the junction box with the supplied **Mounting Screws (B)**. The side of the **Mounting Bracket** marked **Gnd** must face outward.
4. Connect the **BLACK supply wire** to the **Black wire** of the fixture with supplied **Wire Nuts** ensuring a secure connection.
5. Connect the **WHITE supply wire** to the **White wire** from the fixture a secure with supplied **Wire Nuts**.
6. Attach the **ground (GREEN) wire** from the fixture to the **outlet box ground terminal** (or to the box ground wire) or to the **Green Screw** on the **Mounting Bracket**.
7. Secure all **wire nuts connections** with **UL listed electrical tape**. Tuck wires carefully into Junction box.
8. Fit the fixture canopy (**D**) over the **Mounting Bracket(A)**. Insert the **Two Screws (C)** through the designated holes in the **Canopy (D)**. Secure with the supplied **Nuts**.
9. Restore electricity and check the operation of your new lighting fixture.

**Cord and Plug operation**

1. Secure the **Mounting Bracket (A)** to the junction box with the supplied **Mounting Screws (B)**. The side of the **Mounting Bracket (A)** marked **Gnd** must face outward.
2. Fit the fixture canopy over the **Mounting Bracket (A)**. Insert the **Two Screws (B)** through the designated holes in the **Canopy (D)**.
3. **Insert the Plug into an electrical socket and check the operation of your new fixture**

a c c e s s

L I G H T I N G

